

CWDM-A2A8xxLCR-B Series

Add/Drop Mux Coarse Wavelength Division Multiplexing (CWDM)

1 Channel with E/W Lines



CWDM-A2A857LCR-B

Transition Networks CWDM products use a passive technology that allows for any protocol to be transported over the fiber link, as long as it is at a specific wavelength. Transition Networks' CWDM Mux/Demux and Add/Drop Mux can provide a simple and affordable method to maximize existing fiber capacity with little or no increased cost.

Features

- Increase bandwidth on existing fiber infrastructure
- Alleviate fiber exhaustion
- Transmit multiple protocols over an existing duplex fiber link by combining the fiber outputs of multiple media converters
- Provide scalable bandwidth of up to 10 Gbps per channel over existing fiber links
- Plug-and-Play, no configuration of CWDM components
- Use existing standard optical ports on switches and routers
- Utilize Optical Line Converter as transponder
- 1 RU rack mountable chassis to hold 2 CWDM modules

Specifications

Channel Wavelength	ITU & ITU+1 (1260-1620nm)	
Center Wavelength Accuracy	±0.5 (nm)	
Channel Spacing	20 (nm)	
Channel Passband bandwidth (nm)	±6.5 (nm)	
Insertion Loss 1-Channel	In-Drop	< 0.9 dB
	Add-Out	< 0.9 dB
	In-Out	< 0.8 dB
Channel Ripple	0.3dB	
Isolation Adjacent	> 30dB	
Non-Adjacent	> 40dB	
Insertion Loss Temperature Sensitivity	≤ 0.005dB/°C	
Wavelength Temperature Shifting	<0.002 nm/°C	
Polarization Dependent Loss	<0.1dB	
Polarization Mode Dispersion	<0.1 PS	
Directivity	>50dB	
Return Loss	>50 dB	
Mounting	19" Rack Mount	
Dimensions	Width: 8.46" [215 mm]	
	Depth: 7.68" [195 mm]	Height: 1.24" [31.5 mm]
With Chassis	Width: 17.44" [443 mm]	
	Depth: 9.84" [250 mm]	Height: 1.73" [44 mm]
Environment	Operating: -20°C to +70°C Storage: -40°C to +85°C	
Weight	0.88 lbs [0.40 kg]	
Warranty	Lifetime	



Ordering Information

Add/Drop Mux

CWDM-A2A831LCR-B
1 Channel 1310nm port with E/W lines

CWDM-A2A833LCR-B
1 Channel 1330nm port with E/W lines

CWDM-A2A835LCR-B
1 Channel 1350nm port with E/W lines

CWDM-A2A837LCR-B
1 Channel 1370nm port with E/W lines

CWDM-A2A839LCR-B
1 Channel 1390nm port with E/W lines

CWDM-A2A841LCR-B
1 Channel 1410nm port with E/W lines

CWDM-A2A843LCR-B
1 Channel 1430nm port with E/W lines

CWDM-A2A845LCR-B
1 Channel 1450nm port with E/W lines

CWDM-A2A847LCR-B
1 Channel 1470nm port with E/W lines

CWDM-A2A849LCR-B
1 Channel 1490nm port with E/W lines

CWDM-A2A851LCR-B
1 Channel 1510nm port with E/W lines

CWDM-A2A853LCR-B
1 Channel 1530nm port with E/W lines

CWDM-A2A855LCR-B
1 Channel 1550nm port with E/W lines

CWDM-A2A857LCR-B
1 Channel 1570nm port with E/W lines

CWDM-A2A859LCR-B
1 Channel 1590nm port with E/W lines

CWDM-A2A861LCR-B
1 Channel 1610nm port with E/W lines

Optional Accessories (sold separately)

CWDM-MB19R2
19" Rack Mount chassis, 1RU High, holds 2 CWDM Modules

Note: 1310nm channel is wideband (±50nm)