

Mini-Coax 8 CHANNEL BLOCK STRAIGHT

23C12J-40ML5

Electrical data

Impedance	50 Ω
Frequency	DC to 20 GHz
Return loss	≥ 25 dB, DC to 3 GHz ≥ 20 dB, 3 GHz to 6 GHz ≥ 14 dB, 6 GHz to 20 GHz
Insertion loss	≤ 0.02 x √f(GHz) dB
Insulation resistance	≥ 1 x10 ³ MΩ
Center contact resistance	≤ 10 mΩ
Outer contact resistance	≤ 3 mΩ
Test voltage (at sea level)	750 V rms
Working voltage (at sea level)	500 V rms
RF-leakage	≥ 80 dB up to 1 GHz ≥ 60 dB up to 4 GHz

- Connector only, Return loss in application depends decisive on PCB layout -

Mechanical data

Mating cycles	≥ 500
Engagement force	max. 32 N typical 20 N
Extraction force	max. 48 N typical 42 N

Environmental data

Temperature range	-40°C to +125°C
Climatic class	IEC 60068-2-1 40/85/21 IEC 60068-2-2 IEC 60068-2-3
Mechanical shock	IEC 60068-2-27 50G halfsinus, 2 shocks/axis during 11 sec.
Max. soldering temperature 2002/95/EC (RoHS)	IEC 61760-1, +260°C for 10 sec. compliant

Tooling

N/A

Suitable cables

N/A

Packing

Standard	50 pcs in blister
Weight	3.30 g/pce

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Draft	Date	Approved	Date	Rev.	Engineering change number	Name	Date
Armin Maiwalder	08/06/09	Herbert Babinger	06/12/12	a00	12-s486	M. Rahberger	06/12/12
Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany www.rosenberger.de						Tel.: +49 8684 18-0 Fax: +49 8684 18-499 email: info@rosenberger.de	
						Page 2 / 2	