MACOM

Termination Insensitive Mixer, 1 - 1500 MHz

Features

- Third Order Intermodulation Ratio is Insensitive to Port Mismatches
- Conversion Loss: 7 dB Typical Midband
- VSWR: Typically Less than 1.5:1 @ Midband
- Impedance: 50 Ohms Nominal
- Maximum Input Power: 350 mW Max @ 25°C, Derated to 85°C @ 3.5 mW/°C
- MIL-STD-883 Screening Available

Description

The unique design of the termination insensitive mixer (TIM) enables it to apply high reverse voltage to diodes during their "off" phase, in the LO cycle. This allows for higher power level performance with minimum distortion. In addition the TIM has internal loads that provide a good match and also absorb mixer generated LO frequency terms. Combined, these features give the mixer its insensitivity to external mismatches, plus superior VSWR.



Dimensions in 0 are in mm Unless Otherwise Noted: .XXX = +0.010 (.XX = +0.25) .XX = +0.02 (X = +0.5) WEIGHT (APPROX: 0.23 OUNCES = 6.5 GRAMS

Pin Configuration

RH-3

Pin No.	Function	Pin No.	Function	
1	LO	5	GND	
2	GND	6	GND	
3*	IF	7*	IF	
4	GND	8	RF	

* P3 and P7 are connected together to make IF Port.

1

Rev. V3

M/A-COM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit www.macom.com for additional data sheets and product information.

Termination Insensitive Mixer, 1 - 1500 MHz

Rev. V3

Electrical Specifications¹: $T_A = -55^{\circ}C$ to +85°C

Parameter	Test Conditions	Frequency	Units	Min	Тур	Мах
Frequency Range	RF, LO Ports IF Port (3 dB BW)	1 - 1500 1 - 1000	MHz MHz	_	_	_
Conversion Loss ²		5 - 1000 MHz 1 - 1500 MHz	dB dB	_	_	7.5 9.0
Isolation	LO to RF	1 - 5 MHz 5 - 500 MHz 500 - 1500 MHz	dB dB dB	20 28 25		
	LO to IF	1 - 5 MHz 5 - 500 MHz 500 - 1500 MHz	dB dB dB	20 28 17		
	RF to IF	1 - 5 MHz 5 - 500 MHz 500 - 1500 MHz	dB dB dB	20 25 17		
RF Input	1 dB Compression ³ 1 dB Desensitization ³	—	dBm dBm	_	+15 +13	_
SSB Noise Figure	Within 1 dB of Conversion Loss Max	_	_	_	_	_
3rd Order Input Intercept	P _{LO} +13 dBm P _{LO} +20 dBm	15 MHz 500 MHz 1000 MHz 15 MHz 500 MHz 1000 MHz	dBm dBm dBm dBm dBm dBm		+18 +20 +19 +23 +25 +25	
3rd Order Intercept Degradation	@ IF VSWR 3.0:1	—	dB	_	3	_

All specifications apply when operated at +13 dBm available LO power with 50 Ohm source and load impedance.
For IF Frequencies of 5 - 1000 MHz and RF of -10 dBm or less.

3. These characteristics apply @ 25 dBm LO power. This product contains elements protected by United States Patent Number 4,224,572.

Typical Performance Curves



2

M/A-COM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit www.macom.com for additional data sheets and product information.

MD-160



Rev. V3

Termination Insensitive Mixer, 1 - 1500 MHz

Typical Performance Curves

3rd Order intercept vs. IF Port Termination



IF Port Response



Ordering Information

Part Number	Package
MD-160 PIN	RH-3



3rd Order Intercept

VSWR



³

M/A-COM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit www.macom.com for additional data sheets and product information.