P993

Low Range Differential Pressure PCB Mount Sensor

Description

The P993 series of pressure sensors incorporates a silicon capacitive sensing element in a compact package. Using a 5 VDC input, the sensors provide a 0.25 to 4.0 VDC output proportional to pressure. Internal temperature compensation provides an accurate, easy to use device. The innovative design eliminates mounting position effects found on other low pressure differential sensors currently available in the market.



Features

- Rugged PCB Mount Package
- Amplified Temperature Compensated
- Linear Output
- No Position Sensitivity
- EMI/RFI & ESD Protected
- Superior Output Signal Stability

Applications

- Variable Air Volume Systems (VAV)
- Filter Pressure Monitoring Duct Air
- Flow Modulated Furnace Controls
- Combustion Air Flow Gaseous
- Leak Detection



MAIN FEATURES

Pressure Ranges	2, 5, 10, ±1, ±2, ±5 Inches of H20
Electrical Connection	3 solderable pins, tin plated
Pressure Connection	1/8" diameter tube fitting with barb
Housing Material	PET 30% glass reinforced, flame retardant
Output Signal	0.25 VDC – 4 VDC



Pressure Ranges

From 0 to	Inch of H2O	2	5	10	±1	±2	±5
Proof Pressure	PSI	1	1	1	1	1	1
Burst pressure	PSI	1.5	1.5	1.5	1.5	1.5	1.5

Sensata

Technologies



Physical

Operating Life Cycle	min. 10 million full pressure cycles over the full range
Vibration Resistance	1 G from 20 to 1200 Hz
Shock Resistance	10 G's at 6 ms duration
Drop Test	1m onto concrete surface
Weight	< 20 grams (without mating connector)
Operating Temperature	-10°C to + 60°C
Storage Temperature	- 40°C to + 95°C
Media	Air

Performance

Total Error Band	$\pm 2\%$ of span Max. ($\pm 3\%$ for 0 - 1" range) (10°C $\leq T \leq 40$ °C)
------------------	---

Electrical

Output Signal	0.25 to 4 VDC Ratiometric	
Power Consumption	≤ 20 mW	
Operating Supply Signal	5 VDC ± 5%	
Overvoltage Protection	min. 16 VDC	
Short-circuit Proofness	Yes *1	
Reverse Polarity Protection	Yes *2	
Output Impedance	100 Ω Max	

2. for min. 3 intervals at 5 minutes each 3. for min. 10 seconds on assigned pins







