


PCI-8134A

Entry-level 4-axis Servo & Stepper Motion Controller



Features

- 32-bit PCI bus, Rev. 2.2, 33 MHz
- Pulse output rates up to 2.4 MHz
- Pulse output options: OUT/DIR, CW/CCW
- Encoder input frequency up to 2.4 MHz under 4 x AB mode
- 2 axes linear interpolation
- Programmable acceleration and deceleration time
- Trapezoidal and S-curve velocity profiles
- Easy interface to any stepping motors, AC or DC servo, linear or rotary motors
- 28-bit up/down counter for incremental encoder
- All digital inputs and outputs are 2500 VRMS isolated
- Change speed override
- Multi-axis, simultaneous start/stop
- Dedicated I/O interface for PEL, MEL, ORG, EZ, INP, ERC, ALM
- Programmable interrupt sources
- Manual pulser input interface
- Supports up to 12 cards in one system
- 3 ASIC-based home return modes and 9 software-based home return modes
- More than 75 thread safe API functions

Software Support

- **OS Information**
 - Windows® 8/7/XP
 - Linux
 - RTX 5.x/6.x/8.1a
- **Software Compatibility**
 - VB/VC++/BCB/Delphi
 - Various sample programs with source codes
- **Software Recommendations**
 - MotionCreatorPro

Specifications

Pulse Type Motion Control

■ Number of Axes	4
■ Pulse Output Rate	0.01 pps to 2.4 Mpps programmable
■ Pulse Command Output	DIR/OUT, CW/CCW
■ Max. Acceleration Rate	245Mpps2
■ Speed Resolution	16-bit
■ Encoder Input Rate	2.4 MHz @ 3 M cable
■ Encoder Counter Resolution	28-bit
■ Positioning Range	-134,217,728 to +134,217,727 pulses (28-bit)
■ Max. Number of Cards in One System	12

Motion Interface I/O Signals

■ I/O Pin	Differential and 2500 VRMS optically isolated
■ Incremental Encoder Signals Input Pin	DIR/OUT, EA/EB
■ Encoder Index Signal Input	EZ
■ Mechanical Limit Switch Signal Input Pin	±EL, SD, and ORG
■ Servomotor Interface I/O Pin	INP, ALM, ERC, SVON, RDY
■ Pulser Signal Input	PA and PB
■ Simultaneous Start/Stop Signal I/O Pin	STA and STP

Ordering Information

■ PCI-8134A

Entry-level 4-axis servo& stepper motion controller

Accessories

For more information on terminal boards & cables, please refer to page 6-31.

Terminal Boards

■ DIN-100S-01

Terminal board with one 100-pin SCSI-II connector and DIN-rail mounting

■ DIN-814-GP

Terminal board with 100-pin SCSI-II connector for general purpose

■ DIN-814M0

Terminal board for Mitsubishi MR-J2S-A servo amplifier

■ DIN-814M-J3A0

Terminal board for Mitsubishi MR-J3A/J4A servo amplifiers

■ DIN-814Y0

Terminal board for Yaskawa Sigma V servo amplifier

■ DIN-814P-A40

Terminal board for Panasonic MINAS A4/A5 servo amplifiers

Cabling

■ ACL-102100-1

100-pin SCSI-II cable
(mating with AMP-787082-9), 1 M

Pin Assignment

PCI-8134A Pin Assignment of the 100-pin SCSI-type Connector

EX+5V	1	51	EX+5V
EXGND	2	52	EXGND
OUT 1+	3	53	OUT 3+
OUT 1-	4	54	OUT 3-
DIR 1+	5	55	DIR 3+
DIR 1-	6	56	DIR 3-
SVON1	7	57	SVON3
ERC1	8	58	ERC3
ALM1	9	59	ALM3
INP1	10	60	INP3
RDY1	11	61	RDY3
EXGND	12	62	EXGND
EA1+	13	63	EA3+
EA1-	14	64	EA3-
EB1+	15	65	EB3+
EB1-	16	66	EB3-
EZ1+	17	67	EZ3+
EZ1-	18	68	EZ3-
EX+5V	19	69	EX+5V
EXGND	20	70	EXGND
OUT2+	21	71	OUT4+
OUT2-	22	72	OUT4-
DIR2+	23	73	DIR4+
DIR2-	24	74	DIR4-
SVON2	25	75	SVON4
ERC2	26	76	ERC4
ALM2	27	77	ALM4
INP2	28	78	INP4
RDY2	29	79	RDY4
EXGND	30	80	EXGND
EA2+	31	81	EA4+
EA2-	32	82	EA4-
EB2+	33	83	EB4+
EB2-	34	84	EB4-
EZ2+	35	85	EZ4+
EZ2-	36	86	EZ4-
+EL1	37	87	EL3+
-EL1	38	88	EL3-
PSD1	39	89	PSD3
MSD1	40	90	MSD3
ORG1	41	91	ORG3
EXGND	42	92	EXGND
+EL2	43	93	EL4+
-EL2	44	94	EL4-
PSD2	45	95	PSD4
MSD2	46	96	MSD4
ORG2	47	97	ORG2
EXGND	48	98	EXGND
EXGND	49	99	EX+24V
EXGND	50	100	EX+24V