
## **OPERATION**


When voltage is applied to the input, the internal relay energizes and the ON time (T1) begins. Upon completion of the ON time, the relay de-energizes and the OFF time (T2) begins. At the completion of the OFF time, one ON/OFF cycle is completed. This cycling action continues until voltage is removed from the input. The ON/OFF ratio is adjustable from 0 to 100 percent of time base. 0% is OFF; 100% is ON. Reset is accomplished by interrupting the input voltage.






# Percentage Timer Relay Output

### **WIRING**



## **DIMENSIONS** (INCHES)



#### MODEL NUMBER

| MODEL NUMBER        | TDP |     | Α |   |   |     |
|---------------------|-----|-----|---|---|---|-----|
| SUPPLY VOLTAGE      |     |     |   |   |   |     |
| 24 VAC or DC        |     | 24  |   |   |   |     |
| 110/120 VAC or DC   |     | 120 |   |   |   |     |
| TYPE OF OPERATION   |     |     |   |   |   |     |
| Knob Adjustable     |     |     |   | K |   |     |
| Lock Nut Adjustable |     |     |   | L |   |     |
| ENCLOSURE STYLE     |     |     |   |   |   |     |
| 8-pin octal plug-in |     |     |   |   | Α |     |
| Blade plug-in       |     |     |   |   | В |     |
| TIME BASE           |     |     |   |   |   |     |
| 60 sec              |     |     |   |   |   | 060 |
| 300 sec             |     |     |   |   |   |     |
| 600 sec             |     |     |   |   |   |     |
| 900 sec             |     |     |   |   |   |     |
| 30 min              |     |     |   |   |   | 30m |
| 60 min              |     |     |   |   |   | 60m |

Example: TDP-120-AKA-300—Percentage on/off, 120 Volts AC or DC, knob adjustable, time range from 3 to 300 seconds, 8-pin octal plug-in.

## **SPECIFICATIONS**

|                                  | _        | PDT, 10 A @ 250 VAC or 24 VDC, resistive;<br>11 VA @ 120 VAC, inductive |   |  |  |  |  |
|----------------------------------|----------|---|---|--|--|--|--|
| TIME BASE TOLERANCES             | ±1       | 10%   |   |  |  |  |  |
| REPEATABILITY                    | <b>f</b> | 0.5% typica   | I   |  |  |  |  |
| ADJUSTABILITY                    | ,        | 0 to 100% of time base  |   |  |  |  |  |
| TIME BASE                        |          | See ordering information  |   |  |  |  |  |
| SUPPLY<br>VOLTAGE                |          | 24 or 120 V   | AC or VDC,50/60 Hz;±10%   |  |  |  |  |
| FALSE TRANSFI                    | ER       | No  |   |  |  |  |  |
| REVERSE<br>POLARITY<br>PROTECTED |          | Yes   |   |  |  |  |  |
| POWER CONSUMPTION                |          | 2 watts (approximately)   |   |  |  |  |  |
| TEMPERATURE RATING               |          |   | 32° to 131°F (0° to +55°C)<br>-49° to 185°F (-45° to +85°C)           |  |  |  |  |
| LIFE EXPECTAN                    | ICY      | Mechanical<br>Electrical  | 10 million operations (minimum)<br>100,000 operations<br>@ rated load |  |  |  |  |
| WEIGHT                           |          | 5.6 oz.   |   |  |  |  |  |

#### STANDARD DELAY RANGES AVAILABLE

The chart below shows the standard adjustable time delay ranges available. The part number suffix equals the maximum adjustable delay period of the timer. No letters following the suffix number indicates the delay period in seconds; an M indicates minutes; and an H indicates hours.

#### STANDARD DELAY RANGE CHART

| JIANDAND L            | LLAI MANUL         | CHANI              |  |  |  |  |
|-----------------------|--------------------|--------------------|--|--|--|--|
| PART NUMBER<br>SUFFIX | MINIMUM<br>SETTING | MAXIMUM<br>SETTING |  |  |  |  |
| 010                   | 0.1 seconds        | 10 seconds         |  |  |  |  |
| 030                   | 0.3 seconds        | 30 seconds         |  |  |  |  |
| 060                   | 0.6 seconds        | 60 seconds         |  |  |  |  |
| 100                   | 1 second           | 100 seconds        |  |  |  |  |
| 200                   | 2 seconds          | 200 seconds        |  |  |  |  |
| 300                   | 3 seconds          | 300 seconds        |  |  |  |  |
| 600                   | 6 seconds          | 600 seconds        |  |  |  |  |
| 900                   | 9 seconds          | 900 seconds        |  |  |  |  |
| 30M                   | 18 seconds         | 30 minutes         |  |  |  |  |
| 60M                   | 36 seconds         | 60 minutes         |  |  |  |  |
| 90M                   | 54 seconds         | 90 minutes         |  |  |  |  |
| 2H                    | 1.2 Minutes        | 2 hours            |  |  |  |  |
| 4H                    | 2.4 Minutes        | 4 hours            |  |  |  |  |
| 8H                    | 4.8 Minutes        | 8 hours            |  |  |  |  |
| 12H                   | 7.2 Minutes        | 12 hours           |  |  |  |  |
| 16H                   | 9.6 Minutes        | 16 hours           |  |  |  |  |
| 20H                   | 12 Minutes         | 20 hours           |  |  |  |  |
| 24H                   | 14.4 Minutes       | 24 hours           |  |  |  |  |
|                       |                    |                    |  |  |  |  |

Longer delays available upon request. Consult Factory

### EXTERNAL RESISTANCE SELECTION

On models specified as having the external resistor adjustability feature, the delay period is set by placing resistance across designated pins or terminals. One meg ohm resistance provides the maximum delay on all models. The minimum delay is obtained by jumping the terminals together.

The resistor or potentiometer chosen should be a 1/4 watt or larger.

To determine the resistor value required for a specific time delay, use the following formula:

$$R_{ext} = (T_{des}/T_{max})x 1000$$

R<sub>ext</sub> = Resistance value required to obtain T<sub>des</sub> (in K ohms)

 $T_{des}$  = Desired time delay

 $T_{max} = Maximum delay period of the timer$ 

Example: Model TDC-120-ARC-300; find the external resistance value required for a 240 second delay:

$$R_{ext} = \frac{240}{300} \text{ x } 1000 = 800 \text{ K ohms}$$

#### "FIXED" DELAY OPTION

Most ATC Diversified timers are available with the delay period factory preset ("fixed") for some specified duration. When this option is ordered, the part number should have an "F" in the Type of Operation designation: and the last digits should specify the desired time delay in seconds (S), minutes (M), or hours (H).

Example: TDC 120-AFA-30M—delay-on-operate, 120 Volts AC or DC, 8-pin octal plug-in package with a 30 minute fixed delay.

# **■ OFF/ON DELAY TIMERS**

Included in ATC Diversified's broad line of timers are six (6) models that feature independent OFF/ON delay adjustments. They are TDF, TDH, TDI, TSF, and TSH. Notice in the ordering information section on each of their respective pages the timing range is specified by a three (3) digit suffix. This indicates that both the OFF and ON delay periods have the same timing ranges. Example: TDF-120-ALA-300: Both OFF and ON delay periods are independently adjustable from 3 to 300 seconds.

In the event that two (2) separate delay ranges would be required, the part number is modified to add a slash(/) followed by three (3) more digits. Since the OFF delay (TI) is first in all models, it is specified first in the part number. Example: TDF-120-ALA-12H/30M: the OFF delay is adjustable from 7.2 minutes to 12 hours and the ON delay is adjustable from 18 seconds to 30 minutes.

NOTE: Combinations of various "types of operation" are available: fixed/adjustable, knob/lock nut, etc. Consult factory.

#### **■ MODEL NUMBER**

| MODEL NUMBER            | LT L   |     |     |   |   |   |   |
|-------------------------|--------|-----|-----|---|---|---|---|
| TIME DELAY              |        |     |     |   |   |   |   |
| SERIES                  |        |     |     |   |   |   |   |
| Relay Output            | D,     | U   |     |   |   |   |   |
| Solid State Output      | 5      | ;   |     |   |   |   |   |
| MODE OF OPERATION       |        |     |     |   |   |   |   |
| SUPPLY VOLTAGE          |        |     |     |   |   |   |   |
| 24 Volts                |        |     | 24  |   |   |   |   |
| 120 Volts               |        |     | 120 |   |   |   |   |
| 240 Volts               |        |     | 240 |   |   |   |   |
| TYPE OF VOLTAGE         |        |     |     |   |   |   |   |
| AC                      |        |     |     | Α |   |   |   |
| DC                      |        |     |     | D |   |   |   |
| TYPE OF OPERATION       |        |     |     |   |   |   |   |
| Knob Adjustment         |        |     |     |   | K |   |   |
| Lock Nut Adjustment     |        |     |     |   | L |   |   |
| Fixed (Factory Preset)  |        |     |     |   | F |   |   |
| External Resistor Adjus | table  |     |     |   | R |   |   |
| ENCLOSURE STYLE         |        |     |     |   |   |   |   |
| 8 or 11-pin Round Plug  | g-in   |     |     |   |   |   | Α |
| Blade Plug-in           |        |     |     |   |   | В |   |
| Potted Cube             |        |     |     |   |   | С |   |
| DELAY PERIOD            |        |     |     |   |   |   |   |
| See Standard Delay Rai  | nge Ch | art |     |   |   |   |   |

NOTE: Not all time delays are available with each option shown above. The specific options for each timer type are described on their respective pages.