



All dimensions are in mm; tolerances according to ISO 2768 m-H

**Interface**

According to Rosenberger P-SMP

**Documents**

Application note AN001 "Calibration Services"

**Material and plating**

**Connector parts**

Center conductor  
Outer conductor  
Dielectric

**Material**

CuBe  
CuBe or equiv.  
PS

**Plating**

Gold, min. 1.27 µm, over nickel  
Gold, min. 1.27 µm, over nickel

Dieses Dokument ist urheberrechtlich geschützt • This document is protected by copyright • Rosenberger Hochfrequenztechnik GmbH & Co. KG

RF\_35/09;14/6.2

**Electrical data**

Frequency range	DC to 10 GHz
Return loss	≤ 0.20 dB, DC to 4 GHz ≤ 0.35 dB, 4 GHz to 10 GHz
Error from nominal phase <sup>1</sup>	≤ 2°, DC to 4 GHz ≤ 4°, 4 GHz to 10 GHz

<sup>1</sup> The nominal phase is defined by the Offset Delay, the Offset Loss and the Fringing Capacitances

**Mechanical data**

Mating cycles	≥ 100
Engagement force:	
- Full detent	≤ 68 N
Disengagement force:	
- Full detent	≥ 25 N
Gauge	0.00 mm to 0.05 mm

**General standard definitions**

For proper operation the vector network analyzer (VNA) needs a model describing the electrical behaviour of this calibration standard. The different models, units, and terms used will depend on the VNA type and they will have to be entered into the VNA. All values are based on typical geometry and plating.

Offset Z <sub>0</sub> / Impedance / Z <sub>0</sub>	50 Ω
Offset Delay	23.3495 ps
Length (electrical) / Offset Length	7.00 mm
Offset Loss	2.20 GΩ/s
Loss	0.0089 dB/√GHz
Fringing Capacitances <sup>2</sup>	

<sup>2</sup> Fringing Capacitances are determined individually for each open circuit and are documented in a Calibration Certificate.

**Environmental data**

Operating temperature range <sup>3</sup>	+20 °C to +26 °C
Rated temperature range of use <sup>4</sup>	0 °C to +50 °C
Storage temperature range	- 40 °C to +85 °C

RoHS compliant

<sup>3</sup> Temperature range over which these specification are valid.

<sup>4</sup> This range is underneath and above the operating temperature range, within the open circuit is fully functional and could be used without damage.