In-Series Adapters

TNC Types

TNC Male Plug to TNC Female Jack

Model Number


ADT-2596-MF-TNC-02

SPECIFICATIONS

Frequency: DC - 18.0 GHz VSWR: 1.05 @ DC - 4.0 GHz 1.10 @ 4.0 - 8.0 GHz 1.15 @ 8.0 - 18.0 GHz

Impedance: 50 Ohms

Finish: Passivated Stainless Steel





TNC Female Jack to TNC Female Jack

Model Number


ADT-2598-FF-TNC-02

SPECIFICATIONS

Frequency: DC - 18.0 GHz VSWR: 1.05 @ DC - 4.0 GHz 1.10 @ 4.0 - 8.0 GHz 1.15 @ 8.0 - 18.0 GHz

Impedance: 50 Ohms

Finish: Passivated Stainless Steel





TNC Male Plug to TNC Male Plug

Model Number


ADT-2597-MM-TNC-02

SPECIFICATIONS

Frequency: DC - 18.0 GHz VSWR: 1.05 @ DC - 4.0 GHz 1.10 @ 4.0 - 8.0 GHz 1.15 @ 8.0 - 18.0 GHz

Impedance: 50 Ohms

Finish: Passivated Stainless Steel





TNC Female Jack to TNC Female Jack - Flange Mount

Model Number

ADT-2826-FF-TNC-02

SPECIFICATIONS

Frequency: DC - 18.0 GHz VSWR: 1.05 @ DC - 4.0 GHz 1.10 @ 4.0 - 8.0 GHz 1.15 @ 8.0 - 18.0 GHz

Impedance: 50 Ohms

Finish: Passivated Stainless Steel

